

Produktinformation



Information

<i>Tillverkare</i>	Schneider Electric
<i>Artnr</i>	SMC1000I-2UC

APC Smart-UPS C - UPS (rack-mountable) - AC 230 V - 600 Watt - 1000 VA - USB, serial - output connectors: 6 - 2U - black - with APC SmartConnect - for P/N: AR4018SPX432, AR4024SP, AR4024SPX429, AR4024SPX431, AR4024SPX432, NBWL0356A

Specifikation

General

Device Type	UPS - rack-mountable
Height (Rack Units)	2U
Colour	Black
Bundled with	APC SmartConnect

Power Device

UPS Technology	Line interactive
Input Voltage	AC 230 V
Input Voltage Range	AC 180 - 287 V
Input Voltage Range (Adjustable)	AC 170 - 300 V
Frequency Provided	57 - 63 Hz
Frequency Required	50/60 Hz
Input Connectors	1 x power IEC 60320 C14
Output Voltage	AC 230 V \pm 5% - 57 - 63 Hz
Power Capacity	600 Watt / 1000 VA
Output Waveform	Sinewave
Surge Suppression	Yes
Surge Energy Rating	459 Joules
Circuit Protection	Circuit breaker

Battery	
Quantity	1
Technology	Lead Acid
Run Time (Up To)	16 min at half load 6 min at full load
Recharge Time	3 hours
Networking	
Remote Management Interface	USB, serial
Miscellaneous	
Cables Included	Power cable USB cable - external
Rack Mounting Kit	Included
Features	Audible alarm, LCD display, Automatic Voltage Regulation (AVR), cold-start function, automatic shut down reset, automatic self-test, hot-swappable batteries
Compliant Standards	C-Tick, GOST, UL 1449, VDE, RoHS, REACH
Software / System Requirements	
Software Included	Drivers & Utilities
Manufacturer Warranty	
Service & Support	Limited warranty - parts and labour - 2 years
Environmental Parameters	
Min Operating Temperature	0 °C
Max Operating Temperature	40 °C
Humidity Range Operating	0 - 95%
Sound Emission	42 dBA
Dimensions & Weight	
Width	43.2 cm
Depth	40.6 cm
Height	8.9 cm
Weight	20.52 kg
Dimensions & Weight (Shipping)	
Shipping Width	59.4 cm
Shipping Depth	58.4 cm
Shipping Height	24.1 cm
Shipping Weight	22.33 kg
Compatibility Information	
Designed For	P/N: ACCS1000, ACCS1001, ACCS1002, ACCS1003, ACCS1004, ACCS1005, ACCS1006, ACCS1007, ACDC1015, ACDC1016, ACDC1017, ACDC1019, ACDC1020, ACDC1021, ACDC2513, ACF001, ACF002, ACF003, ACF101BLK, ACF102BLK, ACF201BLK,

ACF400, ACF600, AP5017, AP5602, AP5606, AP5607, AP5616,
AP92200, AP9290, AR100, AR100HD, AR202, AR203A, AR204A,
AR2101, AR2102BLK, AR2144BLK, AR2145BLK, AR2200, AR2280,
AR2400, AR2400FP1, AR2401, AR2407, AR2480, AR2487,
AR2487G, AR2500, AR2507, AR2580, AR2587, AR2900, AR2901,
AR3000, AR3100, AR3100G, AR3100SP, AR3100SP1, AR3100SP2,
AR3100TAA, AR3100W, AR3100X609, AR3100X610, AR3100X617,
AR3101, AR3104, AR3104SP1, AR3105, AR3105SP, AR3105W,
AR3107, AR3107G, AR3107SP, AR3107X609, AR3107X610,
AR3107X617, AR3130, AR3140, AR3140G, AR3140W, AR3150,
AR3150SP, AR3150SP1, AR3150SP2, AR3150W, AR3150X609,
AR3150X610, AR3150X617, AR3155, AR3155SP, AR3155W,
AR3157, AR3157SP, AR3157X609, AR3157X610, AR3157X617,
AR3200, AR3300, AR3300G, AR3300SP, AR3300W, AR3300X609,
AR3300X610, AR3300X617, AR3305, AR3305SP, AR3305W,
AR3307, AR3307SP, AR3307W, AR3307X609, AR3307X610,
AR3307X617, AR3340, AR3340G, AR3340W, AR3347, AR3350,
AR3350SP, AR3350W, AR3350X609, AR3350X610, AR3350X617,
AR3355, AR3355SP, AR3355W, AR3357, AR3357SP, AR3357X609,
AR3357X610, AR3357X617, AR4018, AR4018A, AR4018I,
AR4018IA, AR4018IX429, AR4018IX431, AR4018IX432, AR4018SP,
AR4018SPX429, AR4018SPX431, AR4018SPX432, AR4018X429,
AR4018X431, AR4018X432, AR4024, AR4024A, AR4024I,
AR4024IA, AR4024IX429, AR4024IX431, AR4024IX432, AR4024SP,
AR4024SPX429, AR4024SPX431, AR4024SPX432, AR4024X429,
AR4024X431, AR4024X432, AR4038, AR4038A, AR4038I, AR4038IA,
AR4038IX429, AR4038IX431, AR4038IX432, AR4038X429,
AR4038X432, AR7007, AR7050, AR7057, NBWL0356A